



Technical data

Multiphase supply voltage	380 - 415 V 2N/3N
Single-phase supply voltage	220 - 240 V
Frequency	50 Hz
Maximum power consumption	7.6 kW (4.4 kW)
Three-phase power supply/fuse protection	3 x 16 A
Two-phase power supply/fuse protection	2 x 16 A
Single-phase power supply/fuse protection	1 x 32 A
Dimensions (width x depth x height)	760 x 515 x 196 mm
Weight (incl. accessories/packaging)	25 kg
Surface material	SCHOTT CERAN®
Cooktop power levels	1 - 9, P
Power levels	1, 2, P
Size of front cooking zone	Ø 210 mm
Size of rear cooking zone	Ø 175 mm
Front cooking zone output	2300 W
Rear cooking zone output	1400 W
Front cooking zone power setting output	3000 W
Filter medium	Activated charcoal filter with ion exchanger
Maximum filter service life	Max. 150 h / 1 year

product description

- Minimum volume
- Maximum storage space
- Oversized 4 24 cooking surface
- Simple cleaning
- Genuine stainless steel grease filter
- Compact size
- Childproofing feature
- Easy installation
- Extraction power level
- Tried-and-tested compact system

scope of delivery

- GP4 induction cooktop with integrated cooktop extractor
- air inlet nozzle
- stainless steel grease filter
- BAKFS activated charcoal filter set
- Telescopic pull-out with fixing screws
- mounting straps
- sealing tape
- cable routing clips
- height adjustment plate set
- operating and installation instructions
- Power supply cable

accessories

- BAKFS activated charcoal filter set
- BFF stainless steel grease filter
- Air inlet nozzle GP4ED
- UDB25 sealing tape
- BKR760 cooktop frame

Product- and planning instructions

- The cooktop extractor system can be combined with all BORA sockets
- Please note that induction-compatible cookware must be used on induction cooktops
- The connection cable must be provided at the installation site
- Front power socket